

GENERAL DATA

MODEL:	FH 6001
ESP:	6,2 kVA
PRP:	5,6 kVA
VOLTAGE:	230 V
FREQUENCY:	50 Hz
CURRENT:	24,3 A
FUEL:	Petrol
WEIGHT:	69 KG
DIMENSIONS:	790 x 580 x 505 mm



ENGINE

BRAND:	Honda
TYPE:	GX 390
CAPACITY :	389 cm ³
COOLING :	AIR
CYLINDER :	1
STROKE :	4
OIL :	1,1L
STARTING SYSTEM :	Manuel
FUEL :	Petrol
FUEL TANK :	6,1L
CONSUMPTION :	2,7L/H

STANDARD EQUIPMENT

1 socket 230V 16A
1 socket 230V 32A
Oil lever sensor
Overload protection
Oil lever sensor